



HiBOOST

ADAPTADOR SMA-M A N-H



Descripción general

Este adaptador SMA-M a N-F está diseñado para conectar el conector SMA-Hembra y el conector N-Macho.

Características técnicas

- Fácil de instalar
- Exquisita apariencia
- Dimensión optimizada

Technical Parameters	
Insert hole Material	Bronze
Housing Material	Brass
Screw sleeve Material	Brass
Impedance	50Ω
Frequency band	DC-3GHz
Rated operating voltage:	335V
Contact resistance:	
inner conductor	≤ 3mΩ
outer conductor	≤ 2.5mΩ
Insulation resistance	≥ 5000 MΩ
Medium withstand voltage	1000V
Mechanical Characteristics	
Inner conductor separation force	N>0.57N
Mechanical life	>500 times (12 times per minute)
Connecting nut torque	SMA recommended 0.68~1.13N. m
Material of Coaxial Cable	RG187
Working Environment	
Ambient temperature	-55~155°C
Relative humidity	95% at +40°C